
# pH 2700i(X) module

Instruction manual





Order number: 52 121 276





### Warranty

Defects occurring within 1 year from delivery date shall be remedied free of charge at our plant (carriage and insurance paid by sender).

©2005 Subject to change without notice

#### **Return of products under warranty**

Please contact your local Mettler-Toledo representative before returning a defective device. Ship the cleaned device to the address you have been given. If the device has been in contact with process fluids, it must be decontaminated/disinfected before shipment. In that case, please attach a corresponding certificate, for the health and safety of our service personnel.

### **Disposal**

Please observe the applicable local or national regulations concerning the disposal of "waste electrical and electronic equipment".

### **Registered trademarks**

The following registered trademarks are used in this instruction manual without further marking

Calimatic Sensocheck Sensoface ServiceScope VariPower

SMARTMEDIA®

is a registered trademark of Toshiba Corp., Japan

InPro®

is a registered trademark of Mettler-Toledo GmbH, Switzerland

Mettler-Toledo GmbH, Process Analytics, Industrie Nord, CH-8902 Urdorf, Tel. +41 (44) 736 22 11 Fax +41 (44) 736 26 36 Subject to technical changes. Mettler-Toledo GmbH, 09/05. Printed in Germany.



#### Mettler-Toledo GmbH

**Process Analytics** 

Adresse Briefodresse

Im Hackacker 15 (Industrie Nord), CH-8902 Urdorf, Schweiz Postfach, CH-8902 Urdorf

Telefon 01-736 22 11 Telefax 01-736 26 36

www.mt.com
Bank Credit Suisse First Boston, Zürich (Acc. 0835-370501-21-90)

### **Declaration of conformity** Konformitätserkläruna Déclaration de conformité



We/ Wir/Nous

#### Mettler-Toledo GmbH, Process Analytics

Im Hackacker 15 8902 Urdorf Switzerland

declare under our sole responsibility that the product, erklären in alleiniger Verantwortung, dass dieses Produkt, déclarons sous notre seule responsabilité que le produit.

Description

Beschreibung/Description

#### pH 2700i

to which this declaration relates is in conformity with the following standard(s) or other normative document(s).

auf welches sich diese Erklärung bezieht, mit der/den folgenden Norm(en) oder Richtlinie(n) übereinstimmt.

auquel se réfère cette déclaration est conforme à la (aux) norme(s) ou au(x) document(s) normative(s).

**EMC Directive/** EMV-Richtlinie/

Directive concernant la CEM

89/336/EWG

Low-voltage directive/ Niederspannungs-Richtlinie/ Directive basse tension

73/23/EWG

Place and Date of issue/ Ausstellungsort/ - Datum Lieu et date d'émission

Urdorf, September 15, 2005

Mettler-Toledo GmbH, Process Analytics

Waldemar Rauch

1214-62 General Manager PO Urdorf

Thomas Hösli

Head of Operations and R&D

Norm/ Standard/ Standard

EN 61326 / VDE 0843 Teil 20 EN 61010-1 / VDE 0411 Teil 1

METTLER TOLEDO

CE M700 Modul pH 2700i.doc

Sitz der Gesellschaft Mettler-Toledo GmbH, Im Langacher, CH-8606 Greifensee

Warranty	2
Registered trademarks	2
EC Declaration of Conformity	
Intended use	
Safety information	
Software version	10
Modular concept and instruction manuals	11
Short description: M 700 FRONT	
Short description: Menu structure	13
Short description: M 700 BASE	
Parameter tables (Excel) at www.mtpro.com	17
ISM - Intelligent Sensor Management	18
ISM - Plug and Measure	19
ISM - First Calibration	
ISM - Parameter setting	21
ISM - Predictive maintenance	22
ISM - Diagnostics	23
Setting ISM diagnostics messages as favorite	24
Terminal plate	27
Inserting the module	
Wising assessed as	
Wiring examples ISM pH/ORP measurement with glass electrode	20
ISM pH measurement with ISFET sensor	
pH measurement with Sensocheck of glass electrode	
Simultaneous pH and ORP measurement	
ORP measurement with Sensocheck for reference electrode	
Quick start:	
Menu selection, menu structure	34
Passcode entry	
Configuring the measurement display	36

Calibration / adjustment	38
Adjustment	39
Calibration methods	40
Temperature compensation	
Select calibration method	42
Calimatic automatic buffer recognition	
Calibration with manual entry of buffer values	46
Product calibration (calibration with sampling)	
Data entry of premeasured electrodes	
Monitoring functions for calibration	
ORP adjustment	
Temperature dependence of commonly used reference systems	
ISFET zero adjustment	54
Maintenance	56
Setting the module parameters	
Operating levels	57
Enable / lock functions	
Setting the module parameters	
Setting the sensor data parameters	
Sensoface	
Settings of sensor data	
Tolerance adjustment: Program flow	
Activating the tolerance adjustment (SW 700-005)	66
TC process medium	
ORP/rH value	71
Delta function	71
Messages	73
Setting the logbook parameters (System control)	
Logbook	
Factory setting	74

Setting the system control and the outputs (BASE)	
Setting the current output	
Output filter (time constant)	
NAMUR signals (current outputs) - Behavior during messages	79
NAMUR signals (relay contacts):	00
failure, maintenance request, function check	
Relay contacts: protective wiring	
Setting the relay contacts	
Limit value, hysteresis, contact type	83
Setting the OK1, OK2 inputs (BASE)	
Optocoupler inputs (BASE): Usage and switching level	84
Switching parameter sets via OK2 (system control)	
Calculation Blacks (Contamposition)	
Calculation Blocks (System control)	0.0
Calculation of new variables from measured variables	86
Diagnostics functions	89
Device description	
FRONT module	90
BASE module	90
BASE module	
	91
Module diagnostics	91 91
Module diagnostics	91 91 91 92
Module diagnostics  Sensor monitor  ServiceScope (SW 700-004)  Cal timer  Adaptive cal timer	91 91 91 92
Module diagnostics  Sensor monitor  ServiceScope (SW 700-004)  Cal timer  Adaptive cal timer  Tolerance band recorder (SW 700-005)	91 91 91 92 92
Module diagnostics.  Sensor monitor.  ServiceScope (SW 700-004).  Cal timer  Adaptive cal timer.  Tolerance band recorder (SW 700-005).  Cal record.	91 91 92 92 92
Module diagnostics.  Sensor monitor  ServiceScope (SW 700-004)  Cal timer  Adaptive cal timer  Tolerance band recorder (SW 700-005)  Cal record  Sensor network diagram	91 91 92 92 92 93
Module diagnostics.  Sensor monitor.  ServiceScope (SW 700-004).  Cal timer  Adaptive cal timer.  Tolerance band recorder (SW 700-005).  Cal record.	91 91 92 92 92 93
Module diagnostics.  Sensor monitor  ServiceScope (SW 700-004)  Cal timer  Adaptive cal timer  Tolerance band recorder (SW 700-005)  Cal record  Sensor network diagram	91 91 92 92 93 93

## Appendix:

Minimum measuring spans for current outputs	98
Buffer tables	
Buffer set to be entered (SW 700-002)	
Overview of parameter setting	106
Index	111
Overview of icons	115
Overview of menu selection	116

### Intended use

The module is used for simultaneous pH, ORP, and temperature measurement with glass electrodes, ISFET sensors, or sensors with ISM technology (Intelligent Sensor Management). The use of ISFET sensors is an additional function which can be enabled by a separately orderable TAN.

The pH 2700iX module is intended for operation in locations subject to explosion hazards which require equipment of Group II, device category 2(1), gas/dust.

### **Conformity with FDA 21 CFR Part 11**

In their directive "Title 21 Code of Federal Regulations, 21 CFR Part 11, Electronic Records; Electronic Signatures" the US American health agency FDA (Food and Drug Administration) regulates the production and processing of electronic documents for pharmaceutical development and production. This results in requirements for measuring devices used for corresponding applications. The following features ensure that the M 700(X) modular process analysis system meets the demands of FDA 21 CFR Part 11:

### **Electronic Signature**

Access to the device functions is regulated and limited by individually adjustable codes – "Passcodes". This prevents unauthorized modification of device settings or manipulation of the measurement results. Appropriate use of these passcodes makes them suitable as electronic signature.

### **Audit Trail Log**

Every change of device settings can be automatically recorded and documented in the Audit Trail Log on the SmartMedia card. The recording can be encoded.

### **Safety information**

#### Caution!

Never try to open the module! If a repair should be required, return the module to our factory.

If the specifications in the instruction manual are not sufficient for assessing the safety of operation, please contact the manufacturer to make sure that your intended application is possible and safe.

### Be sure to observe during installation:

- Switch off power supply before replacing or inserting a module.
- Protect the signal inputs of the modules against electrostatic discharge.
- Before commissioning it must be proved that the device may be connected with other equipment.
- Observe correct shielding: To avoid interferences, the cable shielding must be completely covered by the ESD shielding cap.

# Application in hazardous locations: pH 2700iX module

When using the M 700 module pH 2700iX, the stipulations for electrical installations in hazardous areas (EN 60079-14) must be observed. When installing the device outside the range of applicability of the 94/9/EC directive, the appropriate standards and regulations in the country of use must be observed. The module has been developed and manufactured in compliance with the applicable European guidelines and standards.

Compliance with the European Harmonized Standards for use in hazardous locations is confirmed by the EC-Type-Examination Certificate. Compliance with the European guidelines and standards is confirmed by the EC Declaration of Conformity.

There is no particular direct hazard caused by the operation of the device in the specified environment.

### **Software version**

pH 2700i(X) module



### **Device software M 700(X)**

The pH 2700i module is supported by software version 6.2 or higher. The pH 2700iX module is supported by software version 6.2 or higher.


### Module software pH 2700i(X)

Software version 1.0 xx.xx.2005

pH module with ISM functionality.

### Query actual device/module software

When the analyzer is in measuring mode: Press **menu** key, open Diagnostics menu.



### Modular concept and instruction manuals

Instruction manuals for basic unit, measuring module, additional functions.

The M 700(X) is an expandable modular process analysis system. The basic unit (M 700 FRONT and BASE) provides three slots which can be equipped by the user with any combination of measuring or communication modules. The software capabilities can be expanded by additional functions (options). Additional functions must be ordered separately. They are supplied with a device-specific TAN for function release.

### M 700(X) modular process analysis system



### Additional functions

Activation via devicespecific TAN For an overview, see www.mtpro.com



#### Measuring modules

- pH / ORP / Temp (also ISM)
- 0<sub>2</sub>/Temp (also ISM)
- Noncontacting conductivity / Temp
- Contacting conductivity / Temp



#### SmartMedia card

Data recording For an overview, see www.mtpro.com.

#### 3 module slots

for free combination of measuring and communication modules

#### **Communication modules**

- Out (additional switching and current outputs)
- PID (analog and digital controller)
- Profibus PA

- The instruction manual for the M 700(X) describes how to install, commission and operate the basic unit.
- The instruction manual for the measuring or communication module describes all functions required for commissioning and working with the respective measuring or communication module.
- **Additional functions** are supplied with a function description.

### **Short description: M 700 FRONT**

M 700

Modular hardware and software system for liquid analysis.

#### 4 captive scews

for opening the analyzer
(**Caution!** Make sure that the gasket
between FRONT and BASE is properly seated and clean!)



#### Transflective LC graphic display

(240 x 160 pixels) white backlighting, high resolution and high contrast.

#### Measurement display

For parameter setting, see Pg 36

#### User interface

with plaintext menus as recommended by NAMUR. Menu texts can be switched to: German, English, French, Italian, Swedish, and Spanish. Intuitively acquirable menu logic, based on Windows standards.

### Secondary displays

see Pg 24

#### 2 softkeys

with context-sensitive functions.

#### Red LED

signals failure (On) or maintenance request/function check (flashing) according to NE 44.

#### Green LED

Voltage supply okay

### Control panel

3 function keys (menu, meas, enter) and 4 arrow keys for menu selection and data entries


### 5 self-sealing cable glands

M20 x 1.5

for entry of voltage supply and signal lines

### **Short description: Menu structure**

Basic functions: Calibration, maintenance, parameter setting, diagnostics



### Legend:

- (1) Pressing the **menu** key accesses menu selection
- (2) Pressing the **meas** key returns to measurement
- (3) Menu groups are selected using the arrow keys
- (4) Press enter to confirm, enter passcode
- (5) Further menu items are displayed
- (6) Selected functions of the Diagnostics menu can be recalled via softkey even when in measuring mode ("Favorites", Pg 24)

### **Short description: M 700 FRONT**

M 700

View into the open device (M 700 FRONT)


#### Slot for SmartMedia card

- Data recording
   The SmartMedia card expands the measurement recorder capacity to > 50000 records.
- Exchange of parameter sets
   5 parameter sets can be stored
   on the SmartMedia card,
   2 of them can be loaded to the M 700
   and switched by remote control.
   Configurations can be transferred
   from one transmitter to the other.
- Function expansions are possible with additional software modules which are released using transaction numbers (TAN).
- Software updates



Each module comes with an adhesive label containing the contact assignments. This label should be sticked to the inner side of the front (as shown).

Then, the terminal assignments remain visible even if further modules are inserted.



Replacing the front module

Pull off power cord and ground wire. To separate the M 700 FRONT from the M 700 BASE, turn the retaining screws of the pivot hinge by 90°.

### The circumferential sealing

guarantees IP 65 protection and allows spray cleaning / disinfection.

Caution! Keep clean!

### **Short description: M 700 BASE**

M 700

View into the open device (M 700 BASE, 3 function modules installed)



#### Module equipment

Module identification: Plug & Play Up to 3 modules can be combined as desired. Several input and communication modules are available.

#### M 700 BASE

2 current outputs (free assignment of process variable) and 4 relay contacts, 2 digital inputs.

VariPower broad-range power supply, 20 ... 265 V AC/DC, suitable for all public mains supplies in the world.

### Power supply units, IS version:

100 ... 230 V AC or 24 V AC/DC

### Warning!

Do not touch the terminal compartment, there may be dangerous contact voltages!

### Important note concerning SmartMedia card

The SmartMedia card may be inserted or replaced with the power supply switched on. Before a memory card is removed, it must be "closed" in the maintenance menu. When closing the device, make sure that the sealing is properly seated and clean.

### **Parameter tables (Excel):**

### www.mtpro.com

### **Parameter tables (Excel)**

2 complete parameter sets can be stored in the basic device M 700(X). You can document the parameter settings of your complete measuring point in an Excel table that can be downloaded from our website.

The complete documentation is available in the download area of our website **www.mtpro.com**.

### ISM - Intelligent Sensor Management



The pH 2700i(X) module allows the connection of sensors with ISM technology.

ISM is an open system that is compatible to existing VarioPin (VP) connection systems and permits the use of

conventional sensors. ISM is not restricted to pH measurement. Sensors from different manufacturers can be connected. During pH measurement it is still possible to continuously monitor the glass and reference electrode.

ISM sensors have an "electronic datasheet" which allows the storage of additional operating parameters such as calibration date and settings directly in the sensor.

An ISM sensor is immediately identified due to the "Plug & Measure" concept. This ensures the clear assignment of a sensor to a measuring point. The risk of confusing the sensors is eliminated. The sensors can be precalibrated in the lab. On-site calibration/adjustment is no more required.

### Information available in the ISM sensor

Each sensor is clearly identified by the unalterable factory data. They consist of information concerning manufacturer, production date, sensor description, application data, and original calibration data, as well as information on predictive maintenance, such as the maximum load index and maximally permitted number of CIP/SIP cycles.

Statistical data inform on the product life cycle of the sensor: data of the last 3 calibrations, adjustment record, buffer values, voltages, temperature, response time, glass and reference impedance.


This allows a comprehensive diagnostic:


- Calculation of the individual load index
- Wear indication
- Adaptive calibration timer


### **ISM - Plug and Measure**



Thanks to the "Plug & Measure" method, an ISM sensor is immediately identified after being connected:







All sensor-typical parameters are automatically sent to the analyzer.

These are, for example, the measurement range, zero and slope of the sensor, but also the type of temperature probe. Without any further parameter setting, measurement starts at once, the measuring temperature is simultaneously detected.


With "Plug & Measure", premeasured ISM sensors can immediately be used for measurement without previous calibration.

The ISM logo is displayed as long as an ISM sensor is connected.

When the ISM sensor has not been adjusted, the "maintenance request" icon is displayed.

A new entry is added to the message list of the Diagnostics menu:

Warn New sensor, adjustment required



# Failure message (incorrect meas. values)

Measured value, alarm icon, and module slot identifier are flashing.


The flashing means:

Caution! The displayed value is no "valid" measured value!

### **First Calibration**



It is possible to use a new sensor without previous calibration. However, a FIrst Calibration is recommended to achieve optimum measurement results.



### Call up calibration

Press **menu** key to select menu.


The "maintenance request" and "calibration" icons are flashing to indicate that calibration is recommended. An entry is made in the message list.

Select calibration using arrow keys, confirm with **enter**. Passcode: 1147.

(To change passcode: Parameter setting/System control/Passcode entry) After passcode entry, the system is in function check mode: Current outputs and relay contacts behave as configured\* and supply either the last measured value or a fixed value until the Calibration menu is exited.

\* The current outputs / relay contacts are configured in the M 700 BASE or the communication modules (Out, PID).

The "function check" mode is indicated by the "Hold" icon (upper left of display).




Select module using arrow keys, confirm with **enter**.

Calibration: See Pg 42.

### **Parameter setting**





Configuring an ISM sensor is considerably safer and easier than configuring a conventional sensor. Since ISM sensors have an "electronic datasheet", many parameters are already provided by the sensor and automatically taken over by the analyzer.

To enter the process-related parameters, select:

- Parameter setting
- Module selection
- Sensor data
- Sensor monitoring details

### Sensor monitoring details (Pg 60)

When an ISM sensor is connected, the values for slope, zero, reference impedance, glass impedance (pH electrodes), and response time are automatically read by the module\*. Additional specifications are required for sensor wear, CIP/SIP counter, autoclaving counter, and sensor operating time. The tolerance limits are displayed in gray.

\* Individual specifications are <u>not</u> overwritten by ISM electrode data.

### **Predictive maintenance**






ISM sensors provide important tools for predictive maintenance.

The settings are made in the

 Maintenance menu / Module selection




#### **Sensor monitor**

for validation of sensor and complete measured-value processing.



### **Temp probe adjustment**

This function is used for compensating for the individual tolerance of the temperature probe and the influence of the lead resistances. Adjustment may only be carried out after the process temperature is precisely measured using a calibrated reference thermometer. The measurement error of the reference thermometer should be less than 0.1 °C. Adjustment without precise measurement might result in considerable deviations of the measured value display!




### **Autoclaving counter (ISM only)**

When setting the sensor data, the maximum number of autoclaving procedures permitted must be specified. Then, each cycle can be recorded in the Maintenance menu. This shows how many autoclaving cycles are still permitted.


### **Diagnostics**








The Diagnostics menu provides single-glance information on the current sensor wear. In addition, the sensor operating time, the number of executed autoclaving, CIP, or SIP cycles, as well as the max. process temperature are indicated.




### Sensor network diagram

- Slope
- Zero
- Reference impedance
- Glass impedance
- Response time
- Calibration timer
- Sensor wear



The measured values are continuously monitored during the measurement process. The sensor network diagram provides at-a-glance information about critical parameters. If a tolerance limit has been exceeded, the respective parameter is flashing.

Values in gray: Monitoring switched off.



The tolerance can be modified as required!

### **Statistics**

Indication of sensor data for the First Calibration (adjustment) and the last 3 calibrations compared to the First Calibration (date and time of First Calibration, zero and slope, impedance of glass and reference electrode, response time).

For ISM, the data are stored in the sensor.

### Setting diagnostics messages as favorite

Select menu: Parameter setting/System control/Function control matrix

### Secondary displays (1)

Here, additional values are displayed in the measuring mode according to the factory setting. When the respective softkey (2) is pressed, the process variables measured by the modules plus date or time are displayed.

In addition, you can use the **softkeys (2)** to control functions. To assign a function to a softkey, select

- Parameter setting/System control/
- Function control matrix (Fig.):


Function which can be controlled by softkeys:

- Parameter set selection
- KI recorder Start/Stop
- Favorites
- EC 400 (fully automated probe controller)

### **Favorites**

Selected Diagnostics functions can be called up directly from the measuring mode using a softkey.

The following table (Pg 25) explains how to select favorites.





#### Example:


- "Favorites" to be selected with
- "Right softkey"

### To select a softkey function:

Select desired function using arrow keys, press "Connect" softkey and confirm with **enter**.

#### Deselect function:

Press "Disconnect" softkey, confirm with **enter**.



#### Note:

When one of the softkeys has been assigned to the "Favorites menu" function, diagnostic functions which have been set as "Favorite" can be directly called up from the measuring mode.

# Practical advantages of ISM sensors (e.g. in biotech applications)

### CIP (Cleaning in Place) / SIP (Sterilize in Place)


CIP/SIP cycles are used for cleaning or sterilizing the process-wetted parts in the process. They are performed for biotech applications, for example. Depending on the application, one (hot acid, water) or more media (hot acid, water, hot alkaline solution, water) are used. The temperatures for CIP are around 80 °C, for SIP around 110 °C.

This procedure extremely stresses the sensors.

ISM sensors can release a message when a preset number of permitted CIP/SIP cycles is exceeded. This allows replacing the sensor in time.


### **Example of CIP cycle:**

The device automatically recognizes the CIP and SIP cycles and correspondingly increments the counter. The user can specify the max. number of cycles and decide whether a message is to be generated when this number is exceeded. These data are not overwritten even after sensor replacement. The number of CIP cycles is shown in the sensor wear monitor of the Diagnostics menu when an individual max value has been specified.




### **Terminal plate pH 2700i(X) module**

### Terminal plate pH 2700i module:



### **Terminal plate pH 2700iX module:**



### Attaching the terminal plates

The terminal plates of the lower modules can be sticked to the inner side of the door.

This facilitates maintenance and service.



### Inserting the module

Note: Be sure to connect the shielding properly!




Terminals 2 and 8 are covered by an ESD shield. To connect the sensor cable, just pull it back. Make sure that the cable glands are tightly closed to protect against humidity.

- **1.** Switch off power supply
- **2.** Open the device (loosen the 4 screws at the front)
- **3.** Place module in slot (D-SUB connector)
- 4. Tighten fastening screws of the module
- 5. Open ESD shielding cap (covering terminals 2 and 8)
- **6.** Connect sensor cable.

  To avoid interferences, the cable shielding must be completely covered by the ESD shielding cap.
- 7. Close ESD shielding cap (covering terminals 2 and 8)
- 8. Close device, tighten screws at the front
- 9. Switch on power supply
- **10.** Set parameters (Pg 59)




pH/ORP measurement with glass electrode and ISM; VP8 connection, Sensocheck of glass and reference electrode



### Note:

Compatible to connection with VP6 (without ISM functionality).

pH measurement with InPro 3300 ISFET sensor




#### Note:

Each time a new sensor is connected, an ISFET zero point adjustment must be performed.

After that, you should perform one of the following calibration methods:


- Calimatic: automatic calibration
- Manual: entry of buffer values
- Data entry: premeasured electrodes

pH measurement with Sensocheck of glass electrode




### Wiring example 4

Simultaneous pH and ORP measurement with Sensocheck of glass and reference electrode




Wiring example ORP measurement with Sensocheck of reference electrode




### Menu selection

After switching on, the analyzer performs an internal test routine and automatically detects the number and type of modules installed. Then, the analyzer goes to measuring mode.



### Menu structure




### **Passcode entry**

### **Enter passcode:**

Select the position using the left/right keys, then edit the number using the up/down keys.
When all numbers have been entered, confirm with **enter**.

### To change a passcode

- Open the menu selection (**menu** key)
- Select parameter setting
- Administrator level, enter passcode
- Select System control: Passcode entry





### **Configuring the measurement display**

Select menu: Parameter setting/Module FRONT/Measurement display

Pressing **meas (1)** returns the analyzer to the measuring mode from any function.

All process variables coming from the modules can be displayed. The table on the next page describes how to configure the measurement display.





**Note:** Function check active

Current outputs and relay contacts behave as configured

Calibration: Detecting deviations without readjustment
 Adjustment: Detecting deviations with readjustment

#### **Caution:**

Without adjustment every pH meter delivers an imprecise or wrong output value! Every pH electrode has its individual zero point and its individual slope. Both values are altered by aging and wear.

To determine the correct pH value, the pH meter must be adjusted to the electrode. The M 700 corrects the voltage delivered by the electrode with regard to electrode zero and slope and displays it as the pH value.

# Be sure to perform an adjustment after having replaced the electrode!

#### **Procedure**

First, a calibration is performed to detect the deviations of the electrode (zero, slope). To do so, the electrode is immersed in buffer solutions whose pH value is exactly known. The measuring module measures the electrode voltages and the buffer solution temperature and automatically calculates the electrode zero and slope. These data are stored in a calibration record. By "Adjustment" the determined calibration data can be used for correction (see following page).

#### **Parameters determined by calibration**

• Zero is the pH value at which the pH electrode outputs the voltage

0 mV. It is different for each electrode and changes with age

and wear.

• Temperature of the process solution must be detected since pH measure-

ment is temperature-dependent. Many electrodes have an

integrated temperature probe.

• Slope of an electrode is the voltage change per pH unit.

For an ideal pH electrode, it lies at -59.2 mV/pH.

## **Adjustment**

See also additional function "Tolerance adjustment" SW700-005, Pg 64.

### **Adjustment**

means that the values determined by a calibration are taken over.


The values determined for zero and slope are entered in the calibration record. (Cal record can be called up in the Diagnostics menu for the pH 2700i(X) module, see Pg 93).

These values are only effective for calculating the measured variables when the calibration has been terminated with an adjustment.

A passcode ensures that an adjustment can only be performed by an authorized person (Administrator).

The Operator can check the current sensor data by a calibration and inform the Administrator when there are deviations.

You can use the additional function SW 700-107 for granting access rights (passcodes) and for AuditTrail (continuous data recording and backup according to FDA 21 CFR Part 11).



Calibration methods

#### **One-point calibration**

The electrode is calibrated with one buffer solution only.

Here, only the electrode zero point is detected and taken into account by the M 700. One-point calibration is appropriate and permissible whenever the measured values lie near the electrode zero point so that slope changes do not have much of an impact.

#### **Two-point calibration**

The electrode is calibrated with two buffer solutions.

In that case, zero point and slope of the electrode can be detected and taken into account by the M 700. Two-point calibration is required if

- the electrode has been replaced
- the measured pH values cover a wide range,
- there is great difference between the measured pH value and the electrode zero,
- the pH measurement must be very accurate,
- the electrode is exposed to extreme wear.

### **Three-point calibration**

The electrode is calibrated with three buffer solutions.

Zero and slope are calculated using a line of best fit according to DIN 19268.

### **Sensor replacement - First Calibration**

A First Calibration must be performed each time the electrode is replaced. During First Calibration, the electrode data together with the electrode type and serial number are stored as reference values for electrode statistics. The "Statistics" menu of Diagnostics (Pg 93) shows the deviations of zero, slope, glass and reference impedance, and response time of the last three calibrations with respect to the reference values of the First Calibration. This allows evaluation of the drift behavior and aging of the electrode.

**Product calibration** (calibration with sampling) See Pg 48

Temperature compensation

#### Temperature compensation during calibration


There are two important reasons for determining the temperature of the buffer solution:

The slope of the pH electrode is temperature-dependent. Therefore the measured voltage must be corrected by the temperature influence.

The pH value of the buffer solution is temperature-dependent. For calibration, the buffer solution temperature must therefore be known in order to choose the actual pH value from the buffer table.

During parameter setting you define whether cal temperature is measured automatically or must be entered manually:


#### **Automatic temperature compensation**



For automatic cal temp detection, the M 700 measures the temperature of the buffer solution with a temperature probe (Pt 100 / Pt 1000 / NTC 30 k $\Omega$  / NTC 8.55 k $\Omega$ ). If you work with automatic temperature compensation during calibration, a temperature probe connected to the temperature input of the M 700 must be in the buffer solution!


Otherwise, you must select manual entry of calibration temperature. When "Cal temp automatic" is set, "Measured cal temp" appears in the menu.

### Manual temperature compensation




The temperature of the buffer solution must be entered manually in the Calibration menu. Temperature measurement is performed using a glass thermometer, for example. When "Cal temp manual" is set, "Enter cal temp" appears in the menu.

Select calibration method



Calibration pH module: Select calibration method

- (1) Pressing the **menu** key accesses menu selection
- (2) Pressing the **meas** key returns to measurement
- (3) Select Calibration menu group using the arrow keys
- (4) Press **enter** to confirm, enter passcode
- (5) Select "Module pH", confirm with **enter**
- (6) Select calibration method



Calimatic automatic buffer recognition

### **Automatic buffer recognition (Calimatic)**


Automatic calibration using Calimatic is performed with one, two, or three buffer solutions. The M 700 automatically detects the nominal buffer value on the basis of the electrode potential and the measured temperature. Any sequence of buffer solutions is possible, but they must belong to the buffer set defined during parameter setting (Pg 64).


The Calimatic takes the temperature dependence of the buffer value into account. All calibration data is converted using a reference temperature of 25 °C.

**During calibration the M 700 is in function check mode.** Current outputs and relay contacts behave as configured (BASE, Out, PID modules).

#### Caution!

Only ever use fresh, undiluted buffer solutions which belong to the selected buffer set (Pg 64)!





Calibration with manual entry of buffer values

### Calibration with manual entry of buffer values

Calibration with manual entry of buffer values is performed with one, two, or three buffer solutions.

The M 700 displays the measured temperature.

You must then enter the temperature-corrected buffer values. To do so, refer to the buffer table (e.g. on the bottle) and enter the buffer value belonging to the displayed temperature.


Intermediate values must be interpolated.


All calibration data is converted using a reference temperature of 25 °C.

**During calibration the M 700 is in function check mode.** Current outputs and relay contacts behave as configured (BASE, Out, PID modules).

#### **Caution!**

Only ever use fresh, undiluted buffer solutions!





Product calibration

### **Product calibration (calibration with sampling)**


When the electrode cannot be removed – e.g. for sterility reasons – its zero point can be determined with "sampling". To do so, the currently measured process value is stored by the analyzer. Immediately afterwards, you take a sample from the process. The pH value of the sample is measured in the lab or directly on the site using a portable pH meter. The reference value is entered into the measuring system. From the difference between measured value and reference value, the electrode zero point is calculated (this method only allows one-point calibration).

**During calibration the M 700 is in function check mode.** Current outputs and relay contacts behave as configured (BASE, Out, PID).

#### Caution!

The pH value of the sample is temperature-dependent. Therefore, the reference measurement should be performed at the sample temperature shown in the display. Transport the sample in an insulated container. The pH value may also be altered due to escaping of volatile substances.

Menu	Display	Product calibration
cal	Tour ph   Tour	Select module: pH 2700i The M 700 is in function check mode. Current outputs and relay contacts behave as configured (BASE, Out, PID). Confirm with enter.
	☐ 7.00 pH ☐ 25.6 °C ☐ Module pH 2700i ☐ Calimatic: automatic calibration ☐ Manual: entry of buffer values ☐ Product calibration ☐ Data entry: premeasured electrodes ☐ ORP calibration ☐ Return	Select calibration mode "Product calibration"  Confirm with <b>enter</b> .



Calibration by entering data from premeasured electrodes

### **Data entry of premeasured electrodes**

Entry of values for zero point, slope, and isothermal potential of a pH electrode. The values must be known, e.g. determined beforehand in the laboratory.

**Caution!** Input of an isothermal potential V<sub>iso</sub> also applies to the calibration methods

- Calimatic
- Manual entry
- Product calibration

For an explanation of the isothermal potential, refer to Pg 51.

**During calibration the M 700 is in function check mode.** Current outputs and relay contacts behave as configured (BASE, Out, PID modules).


Menu	Display	Manual entry
cal	□ Data entry  ■ When changing sensors perform First cal for statistics!  □ Sensor replacement Zero +07.00pH Slope 058.0 mV/pH Isothermal potential +0000 mV  Return	Select: Data entry of premeasured electrodes (Pg 40) Remove electrode and connect premeasured electrode. Call up "Sensor replacement". Enter the values for • Zero • Slope • Isothermal potential  Return with softkey. Return to measurement with meas

#### **Isothermal potential**

The isothermal intersection point is the point of intersection between two calibration lines at two different temperatures. The potential difference between the electrode zero point and this intersection point is the isothermal potential "V<sub>iso</sub>".

It may cause measurement errors depending on the temperature. These errors can be compensated for by defining the " $V_{\rm iso}$ " value.

Measurement errors are avoided by calibrating at measuring temperature or at a controlled and stable temperature.



### **Monitoring functions for calibration**

The M 700 provides comprehensive functions for monitoring proper calibration performance and the electrode condition. This allows documentation for quality management to ISO 9000 and GLP/GMP.

- Sensocheck monitors the electrode condition by measuring the glass and reference electrode impedances.
- Regular calibration can be monitored by the cal timer (see Pg 67).
- Adaptive cal timer automatically reduces the calibration interval when the electrode is subjected to high stress
- The calibration record (GLP/GMP) provides all relevant data of the last calibration and adjustment.
- The statistics show the behavior of the electrode parameters during the last three calibrations compared to the First Calibration.
- The logbook shows the time and date of a performed calibration

**ORP** adjustment

#### **ORP adjustment**

The potential of a redox electrode is calibrated using a redox (ORP) buffer solution. In the course of that, the difference between the measured potential and the potential of the calibration solution is determined. This potential difference is printed on the calibration solution bottle and is defined as the voltage across the redox electrode and a reference electrode.

Examples: 220 mV Pt against Ag/AgCl, KCl 3 mol/l

427 mV Pt against SHE

During measurement this difference is added to the measured potential.

 $mV_{ORP} = mV_{meas} + \Delta mV$ 

mV<sub>ORP</sub> = displayed oxidation-reduction potential (measured ORP)

mV<sub>meas</sub> = direct electrode potential (ORP input, see Sensor monitor)

 $\Delta$ mV = delta value, determined during calibration

### **ORP related to the standard hydrogen electrode (SHE)**

The oxidation-reduction potential can also be calibrated automatically with respect to the standard hydrogen electrode (SHE). To do so, you must first select the reference electrode used (see parameter setting Pg 68).


The temperature behavior of the reference electrode is automatically taken into account.

You can choose from the following types of reference electrodes:

Ag/AgCl, KCl 1 mol/l (Silver/silver chloride) Ag/AgCl, KCl 3 mol/l (Silver/silver chloride)

Hg, Tl/TlCl, KCl 3.3 mol/l (Thalamid)

Hg/Hg<sub>2</sub>SO<sub>4</sub>, K<sub>2</sub>SO<sub>4</sub> saturated (Mercury sulfate)



Temp dependence of commonly used reference systems measured against SHE

Temperature [°C]	Ag/AgCl/KCl 1 mol/l [ΔmV]	Ag/AgCl/KCl 3 mol/l [ΔmV]	Thalamid [ΔmV]	Mercury sulfate [∆mV]
0	249	224	-559	672
10	244	217	-564	664
20	240	211	-569	655
25	236	207	-571	651
30	233	203	-574	647
40	227	196	-580	639
50	221	188	-585	631
60	214	180	-592	623
70	207	172	-598	613
80	200	163	-605	603

ISFET zero adjustment


### **ISFET zero adjustment**

When measuring with an ISFET sensor (e.g. InPro 3300), the nominal zero point must be adjusted each time a new sensor is connected (to adjust the operating point). The adjustment for that sensor remains stored in the analyzer.

Afterwards, you should perform a two-point calibration using one of the following methods:

- Calimatic: automatic calibration
- Manual: entry of buffer values
- Data entry: premeasured electrodes


**During calibration the M 700 is in function check mode.** Current outputs and relay contacts behave as configured (BASE, Out, PID modules).



### **Maintenance**

Sensor monitor, temperature probe adjustment


Note: Function check active



## **Parameter setting: Operating levels**

Viewing level, Operator level, Administrator level

Note: Function check active (Parameter setting: BASE, Out, PID modules)



# **Parameter setting: Lock functions**

Administrator level: Enable / lock functions for Operator level


**Note:** Function check active (Parameter setting: BASE, Out, PID modules)

Menu	Display	Administrator level: Enable / lock functions
		<b>Example:</b> Blocking access to the calibration adjustments from the Operator level
© m bal	Parameter setting (Administrator)  Ci System control  Ci Module FRONT M 700-011  Ci Module BASE M 700-021  Ci Module pH 2700i  Ci Module PH 2700i  Ci Module Cond Ind 7700  Return	Call up parameter setting Select Administrator level. Enter passcode (1989). Select "Module pH" using arrow keys, confirm with enter.
	☐ 11.03 pH ☐ 25.0°C ☐ Module pH 2700i (Administrator) ☐ Input filter ☐ Sensor data ☐ Cal preset values ☐ TC process medium ☐ ORP/rH value ☐ Delta function  Return ☐ Block	Select "Cal preset values" using arrow keys. "Block" with softkey.
	II 11.03 pH II 25.0°C  II Module pH 2700i (Administrator) II Input filter If Sensor data In Cal preset values If TC process medium If ORP/rH value If Delta function  Return If Release	Now, the "Cal preset values" line is marked with the "lock" icon. This function cannot be accessed from the Operator level any more. The softkey function changes to "Release".
© tro p ay	☐ 11.03 pH ☐ 25.0°C ☐ Module pH 2700i ☐ Input filter ☐ Sensor data ☐ Cal preset values ☐ TC process medium ☐ ORP/rH value ☐ Delta function ☐ Return	Activating parameter setting Select Operator level, passcode (1246). Select "Module pH". Now, the locked function is displayed in gray and marked with the "lock" icon.

### Setting the module parameters

Activating parameter setting

**Note:** Function check active (Parameter setting: BASE, Out, PID modules)




#### **Function check**

During parameter setting the M 700 is in "function check" mode: Current outputs and relay contacts behave as configured. See instruction manuals of BASE, Out, PID communication modules. (Free download at www.mtpro.com).

## Setting the sensor data parameters

Sensor data / Sensor monitoring details


Note: Function check active



### Sensoface @

Sensoface is a graphic indication of the sensor condition.

Prerequisite: Sensocheck must have been activated during parameter setting.



#### Sensocheck:

Automatic monitoring of glass and reference electrode

The "smileys" provide information on wear and required maintenance of the sensor ("friendly" - "neutral" - "sad").

#### Sensoface criteria

Parameter	Auto*	Standard electrodes
Slope	59.2	< 53.3 or > 61
Zero	7.00	< 6.00 or > 8.00
Reference impedance	Rcal **	< 0.3 Rcal or > 3.5 Rcal
Glass impedance	Rcal **	$<$ 0.6 Rcal or $>$ 100 K $\Omega$ + 0.5 Rcal
Response time Fine Medium Coarse		120 sec 80 sec 60 sec
Cal timer		when 80 % expired
Sensor wear		as specified (ISM sensors only)

<sup>\*</sup> Valid for standard electrodes with pH = 7.00.

<sup>\*\*</sup> Rcal is determined during calibration

## **Settings of sensor data**

With "Auto", the tolerance limits for the monitoring criteria are determined by the analyzer. They are then displayed in gray.

With "Individual", these tolerances can be adjusted.

**Note:** Function check active. Gray values (display) cannot be edited.

Parameter	Default	Selection / Range / Notes
Input filter		
Pulse suppression	Off	Off, On (suppression of fast transients at the input)
Sensor data		
• Sensor type	Standard	Standard, Other, ISFET (SW 700-012), ISM (automatically identified)
Temperature detection     Temperature probe     Sensor monitoring details     Slope	Pt 1000	Pt100, Pt1000, NTC30 k $\Omega$ , NTC 8.55 k $\Omega$
Monitoring Nominal Min	Auto 59.2 mV/pH 53.3 mV/pH	Auto, Individual
Max Message • Zero	61.0 mV/pH Maint. request	Off, failure, maintenance request
Monitoring Nominal Min Max	Auto 06.95 pH 05.95 pH 07.95 pH	Auto, Individual
Message • Sensocheck Ref el	Maint. request	Off, failure, maintenance request
Monitoring Nominal Min Max	Auto 025.5 kΩ 015.9 kΩ 112.8 kΩ	Auto, Individual
Message • Sensocheck Glass el Monitoring	Off Auto	Off, failure, maintenance request (not for sensor type ISFET) Auto, Individual
Nominal Min Max	305.0 MΩ 087.1 MΩ 999.9 MΩ	
Message • Response time	Off	Off, failure, maintenance request
Monitoring Response time Max	Auto 0080 s	Auto, Individual
Message	Off	Off, failure, maintenance request

Parameter	Default	Selection / Range / Notes
Sensor wear* Monitoring Measurement quality** Message CIP counter* Monitoring Max. cycles Message SIP counter* Monitoring Max. cycles Message Autoclaving counter* Monitoring Max. cycles Message Sensor operating time* Monitoring Max. operating time Message ISFET leakage current*** Monitoring Max. Message	Auto Normal Maint. request  Off 000 Maint. request  Off 000 Maint. request  Off 000 Maint. request  Off 0000 Maint. request  Auto 1000 nA Maint. request	Off, Auto, Individual High, Normal, Low Off, failure, maintenance request Off, Individual Off, failure, maintenance request Auto, Individual (For ISM: default value from electrode) Off, failure, maintenance request

ISM sensors automatically provide most of the default settings. Individual entries are <u>not</u> overwritten by the ISM sensor.

<sup>\*</sup> Only for ISM

<sup>\*\*</sup> Measurement quality allows the user to take account of the influence of the individual process conditions on the sensor wear.

<sup>\*\*\*</sup> Only available with ISFET additional function (SW 700-012)

### **Setting the cal preset values**

Cal preset values

Note: Function check active

Parameter	Default	Selection / Range
Cal preset values • Calimatic buffer	Mettler-Toledo	Mettler-Toledo: 2.00 4.01 7.00 9.21 Merck/Riedel: 2.00 4.00 7.00 9.00 12.00 DIN 19267: 1.09 4.65 6.79 9.23 12.75 NIST standard: 4.006 6.865 9.180 NIST technical: 1.68 4.00 7.00 10.01 12.46
Drift check	Standard	Fine: 1.2 mV/min (Abort after 180 s) Standard: 2.4 mV/min (Abort after 120 s) Coarse: 3.75 mV/min (Abort after 90 s)
Cal timer     Monitoring     Cal timer     Adaptive cal timer      Tolerance band check     (SW 700-005)	Auto 168 h 0000h (Off) Off	Auto, Off, Individual Off, entry Off, On Tolerance adjustment: Off, On Tolerance band zero +00.20 pH (entry) Tolerance band slope +002.0 mV/pH (entry)

#### **Tolerance adjustment**


(Additional function SW 700-005)

During calibration the tolerance band checks zero and slope and automatically performs an adjustment when the tolerance band is exceeded. The parameters are stored in the tolerance band recorder (Diagnostics menu). The additional function SW 700-005 is device-specific. When ordering an additional function, you therefore have to specify the serial number of your M 700 FRONT in addition to the respective order number.

(The M 700 FRONT contains the M 700 system control).

The manufacturer then supplies a TAN (transaction number) to release the additional function in the system control menu (see Pg 66).


# SW 700-005: Tolerance adjustment Program flow



## Activating the tolerance adjustment

Select menu: Parameter setting/System control/Release of options


Note: The TAN for releasing an additional function is only valid for the device with the corresponding serial number!



## Setting the cal preset values

Cal preset values: Calimatic buffer, cal timer, cal tolerance band

Note: Function check active




Default settings and selection range

**Note:** Function check active

Parameter	Default	Selection / Range
TC process medium • TC correction	Off	Off, linear, ultrapure water, table, Linear: enter temperature factor +XX.XX %/K
ORP/rH value • Reference electrode  • ORP conversion to SHE • Calculate rH with factor	Ag/AgCI,KCI 3mol/I No No	Ag/AgCl,KCl 3mol/l Hg, Tl/TlCl, KCl 3.3 mol/l Hg/Hg <sub>2</sub> SO <sub>4</sub> , K <sub>2</sub> SO <sub>4</sub> sat No, Yes No, Yes, entry of factor
Delta function • Delta function	Off	Off, pH, mV+ORP or rH: entry of delta value

TC process medium

Note: Function check active



TC process medium – Linear temperature compensation of process medium

### Temperature compensation of process medium

Linear temperature compensation, reference temp fixed at 25 °C

 $pH_{(25 °C)} = pH_M + TC/100 % (25 °C - T_M)$ 


 $pH_{(25 °C)} = pH$  value compensated to 25 °C

 $pH_M$  = measured pH value (temperature-corrected)

TC = Temperature factor [%/K]  $T_M$  = Measured temperature [° C]

ORP/rH value, delta function, messages

Note: Function check active



# **Setting the message parameters**

Messages: Default settings and selection range

Note: Function check active


Parameter	Default	Selection / Range
Messages  • pH value  • ORP value  • rH value  • Temperature  • mV value	Limits max Off Off Limits max Off	Off, device limits max., variable limits*  *) With "Variable limits" selected, the following parameters can be edited: • Failure Limit Lo • Warning Limit Lo • Warning Limit Hi • Failure Limit Hi

#### **Device limits**

• Device limits max. Maximum measurement range of device

• Variable limits: Range limits specified


#### Device limits max.



# Setting the message parameters

Messages


Note: Function check active



# Logbook, factory setting

Parameter setting/System control/Logbook


Note: Function check active




# **Current outputs, contacts, OK inputs**

Select menu: Parameter setting/Module BASE


Note: Function check active



# Assignment of measured values: Beginning (4 mA) and end (20 mA)



Example 2: Range pH 5 - 7 Advantage: Higher resolution in range of interest




# **Current outputs: Current output curves**

Select menu: Parameter setting/Module BASE


#### Linear characteristic

The measured variable is represented by a linear output current curve.



### • Trilinear characteristic

Two additional corner points must be entered:




### • Note: Bilinear characteristic

For a bilinear characteristic, identical parameters are entered for the two corner points (1st corner, 2nd corner).

#### Function characteristic

Nonlinear output current characteristic: allows measurements over several decades, e.g. measuring very low values with a high resolution and high values with a low resolution.

Required: Entering a value for 50 % output current.



#### **Equation**

Output current (4 to 20 mA) = 
$$\frac{(1+K)x}{1+Kx}$$
 16 mA + 4 mA

$$K = \frac{E + I - 2 * X50\%}{X50\% - I} \qquad x = \frac{M - I}{E - I}$$

I: Initial value at 4 mA

X50%: 50% value at 12 mA (output current range 4 to 20 mA)

E: End value at 20 mA M: Measured value

### Logarithmic output curve over one decade:

*I:* 10 % of maximum value X50%: 31.6 % of maximum value

E: Maximum value

### Logarithmic output curve over two decades

*I:* 1 % of maximum value X50%: 10 % of maximum value

E: Maximum value

# **Output filter**


Time constant

### Time constant of output filter

To smoothen the current output, a low-pass filter with adjustable time constant can be switched on. When there is a jump at the input (100 %), the output level is at 63 % after the time constant has been reached. The time constant can be set from 0 to 120 sec. If the time constant is set to 0 s, the current output follows the input.

#### Note:

The filter only acts on the current output and the current value of the secondary display, not on the measurement display, the limit values, or the controller!



# **NAMUR signals: Current outputs**

Behavior during messages: Function check, 22 mA signal


### **Behavior during messages**



Depending on the parameter setting ("Messages"), the current outputs switch to:

- Currently measured value
- Last measured value (HOLD function)
- Fixed value (22 mA)

In the case of a fault a 22 mA signal can be generated for the selected process variable (1st primary value).



### Message when the current range is exceeded

As delivered, the "Maintenance request" (Warn) message is generated when the current range is exceeded (< 3.8 mA or > 20.5 mA).

This setting can be changed in the Parameter setting menu of the respective measuring module at "Messages".

To generate a "Failure" message, the limit value monitoring must be set to "Variable limits":

Parameter setting - <measuring module> - Messages - Variable limits - Failure limit ...

Enter the same values for the failure limits as for the current output: Parameter setting - Module BASE - Output current - Variable Start / End.


# **NAMUR signals: Relay contacts**

Failure, maintenance request, function check

As delivered, the floating relay outputs of the M 700 BASE are assigned to the NAMUR signals:

• Failure Contact K4, Normally closed contact (signaling current failure)

Maint. request
 Function check
 Contact K3, normally open contact
 Contact K2, normally open contact



#### **NAMUR signals:** Factory setting of contacts

- Select parameter setting
- Administrator level
- Select "Module BASE" (Fig.)

You can define a delay time for "Maintenance request" and "Failure", resp. If an alarm message is released, the contact will only be activated after expiry of this delay time

#### Failure is active

when a value has exceeded (or fallen below, resp.) a preset "Failure Limit Hi" or "Failure Limit Lo", when the measured value is out of range or in the event of other failure messages. That means that the equipment no longer operates properly or that process parameters have reached a critical value. Failure is disabled during function check.

#### Maintenance request is active

when a value has exceeded (or fallen below, resp.) a preset "Warning Limit Hi" or "Warning Limit Lo", or when other warning messages have been activated. That means that the equipment is still operating properly but should be serviced, or that process parameters have reached a value requiring intervention.

Warning is disabled during "Function check".

### Function check is active:


- during calibration
- during maintenance (current source, meas. point maintenance)
- during parameter setting at the Operator level and the Administrator level

• during an automatic rinsing cycle.

# **Relay contacts: protective wiring**

### **Protective wiring of relay contacts**

Relay contacts are subjected to electrical erosion. Especially with inductive and capacitive loads, the service life of the contacts will be reduced. For suppression of sparks and arcing, components such as RC combinations, nonlinear resistors, series resistors and diodes should be used.



# Typical AC applications with inductive load

1 Load

2 RC combination, e.g. RIFA PMR 209 Typical RC combinations

e.g.:

Capacitor 0.1 μF, Resistor 100 ohms / 1 W

3 Contact

### Warning!

Make sure that the maximum ratings of the relay contacts are not exceeded even during switching!


### Information concerning relay contacts

As delivered, the relay contacts are suitable for low signal currents (down to approx. 1 mA). If currents above approx. 100 mA are switched, the gold plating is destroyed during the switching process. After that, the contacts will not reliably switch low currents.

# **Relay contacts**

Parameter setting/Module BASE/Relay contacts

Menu	Display	Setting the relay contacts
week and the second sec	Contact K1 (Administrator)  Usage Measured variabl Limit value Hysteresis Effective direction Contact type Return  7.00 pH 19.2°C  7.00 pH 19.2°C  NAMUR maintenance NAMUR function check Limit value Rinse contact Parameter set 2 active USP output	Relay contacts, usage  Call up parameter setting  Enter passcode  Select "Module BASE"  Select "Contact"  "Usage" (Fig.)



The M 700 BASE provides 4 relay contacts (max. AC/DC rating 30 V / 3 A each). Contact K4 is provided for failure message. The switching behavior (normally open or normally closed), as well as a switch-on or switch-off delay can be defined.

Default settings of the user-definable relay contacts of the M 700 BASE:

K3: NAMUR maintenance request

K2: NAMUR function check

K1: Limit value


The contact assignment K1 - K3 is user defined ("Usage"):

- NAMUR maintenance request
- NAMUR function check
- Limit value
- Rinse contact
- Parameter set 2 active
- USP output (COND module only)

**Contact assignment:** See terminal plate of M 700 BASE

# Limit value, hysteresis, contact type

Parameter setting/Module BASE/Relay contacts/Usage



#### Limit value




Effective direction min

### Limit value



Effective direction max



### Icons in the measurement display:

Measured value exceeds limit:



Measured value falls below limit: ▼

Signal

### **Hysteresis**

Tolerance band around the limit value, within which the contact is not actuated. Serves to obtain appropriate switching behavior at the output and suppress slight fluctuations of the measured variable (Fig.)


### Contact type

Specifies whether the active contact is closed (N/O) or open (N/C).

# OK1, OK2 inputs: Specify level

Parameter setting/Module BASE/Inputs OK1, OK2


Note: Function check active



The M 700 BASE provides 2 digital inputs (OK1, OK2). The following functions (depending on the parameter setting) can be started via a control signal:

- OK1: "Off" or "Function check"
- OK2: Select: System control /
   Function control matrix.
   ("Off", "Parameter set A/B",
   "Start KI recorder")

The switching level for the control signal must be specified: (active 10...30 V or active > 2 V).



**Contact assignment:** See terminal plate of M 700 BASE

# Switching parameter sets via OK2

Parameter setting / System control / Function control matrix

Note: Function check active

#### **Parameter sets**


2 complete parameter sets (A, B) can be stored in the M 700.

You can switch between the parameter sets using the OK2 input.

The currently activated set can be signaled by a relay contact.

An icon in the measurement display shows which parameter set is active:





#### Note

The selection has no effect when working on SmartMedia card with SW 700-102.

## **Calculation Blocks**

Select menu: Parameter setting/System control/Calculation Blocks Calculation of new variables from measured variables

#### **Calculation Blocks**

Two measuring modules with all their measured values serve as input for the calculation block. In addition, the general device status (NAMUR signals) is taken into account. The analyzer calculates the differences between the existing values.

### **Current outputs**

All current outputs can be set to output the new process variables formed by the Calculation Blocks.


### **Measurement display**

All new process variables can be displayed as primary or as secondary value.


#### **Controller**

Controller functions are not supported.

### **Functionality of measuring module**



### **Functionality of Calculation Block**




# **Activating Calculation Blocks**

Select menu: Parameter setting/System control/Calculation Blocks Combining measuring modules to Calculation Blocks


### **Combining measuring modules**

Two Calculation Blocks can be activated.




# **Configuring a Calculation Block**


Select menu: Parameter setting/System control/Select Calculation Block Setting the process variable to be calculated



# **Diagnostics functions**


General status information of the measuring system Select menu: Diagnostics





# **Module diagnostics**

Module diagnostics, sensor monitor, ServiceScope



# **Module diagnostics**


Calibration timer, Tolerance adjustment, Cal record, Sensor network diagram, Statistics

Menu	Display	Calibration timer, tolerance adjustment
7	7.00 pH 22.3 °C CTime 160h Pavorites menu	Cal timer After expiration of a presettable interval (Parameter setting, Module pH, Cal preset values), the calibration timer generates a warning message as a reminder that calibration is required. The remaining time can be indicated in the measuring mode by pressing a softkey (secondary display: "CTime").
<b>O</b> dlag	☐ 7.00 pH ☐ 22.3 °C ☐ Adaptive cal timer ☐ Next calibration in approx. 102 h (02.08.02 14:08) Default Adaptive Current ☐ 168 h Adaptive Current ☐ 58 h El stress ☐ 5 % Return	Adaptive calibration timer The time until the next due calibration is automatically reduced depending on the electrode stress (temperature, pH value), i.e. old electrode = timer expires sooner.
	☐ 7.00 pH ☐ 22.3 °C ☐ T-band recorder 6.00 ZERO 8.00 50.7 Slope 61.7	Tolerance adjustment (Additional function SW 700-005) Records the tolerance ranges for zero and slope over the time. If the values determined by a calibration exceed the tolerance limits, the calibration is taken over as adjustment. Display can be graphical or as a listing. The tolerance band (zero, slope) is configured during parameter setting (Module pH, Cal preset values).

# Menu Display

# Cal record, sensor network diagram, statistics






Return

Calibration data

#### Cal record

Data of last adjustment/calibration, suitable for documentation to ISO 9000 and GIP/GMP


(Date, time, calibration method, zero and slope, isothermal potential, information concerning calibration buffers and response times)




### Sensor network diagram

Graphical representation of the sensor parameters. Tolerance limit violations can be seen at a glance. Critical parameters are flashing. Parameters displayed in gray have been disabled during parameter setting or do not apply to the currently selected sensor.

The tolerance limits (radius of "inner circle") can be modified as desired. See Parameter setting/ Module pH/Sensor data/ Sensor monitoring details, Pg 62





#### **Statistics**

Indication of sensor data for the First Calibration (adjustment) and the last 3 calibrations compared to the First Calibration.

(Date and time of First Calibration, zero and slope, impedance of glass and reference electrode, response time. For ISM, the data are stored in the sensor)

# **Specifications**

### Specifications M 700 pH 2700i(X)

pH/	OR	Ρi	n	bι	ıt

(EEx ia IIC)

Simultaneous measurement of pH and ORP with glass electrodes or ISFET (InPro 3300),

control of ISM sensors
Input for glass electrode
Input for reference electrode

Input for redox (ORP) electrode or solution GND (SG)

Input for ISFET

2000 mV

Measurement range (MR)

pH value -2.00 ... +16.00 ORP value -2000 ... +2000 mV

rH value 0.0 ... 42.5

Adm. voltage ORP + pH [mV] Adm. cable capacitance Glass electrode input \*\*

< 2 nF (cable length max. 20 m)

Reference electrode input \*\*

Measurement error \*\*\*
(Display)

### Temperature input

(EEx ia IIC)

Measurement range (MR)

Resolution

Measurement error\*\*\*

### 2-wire connection, adjustable

 $0.1~^{\circ}\text{C}$  /  $1~^{\circ}\text{F}$ 

0.2 % meas.val. + 0.5 K (< 1 K with NTC > 100 °C)

### Temp compensation

media-dependent

Reference temp 25 °C

- Linear temperature coefficient, user-defined from 00.00 ... 19.99%/K
- Ultrapure water 0 ... 150 °C
- Table 0 to 95 °C, user-defined in 5 K steps

ORP \* Automatic conversion to standard hydrogen electrode SHE when type of reference electrode is entered Zero adjustment -200 ... +200 mV ORP calibration ' **ISFFT** ISFET sensor standardization (Additional function SW 700-012) Automatic determination of zero offset adm. range -1800 mV to 0 pH sensor standardization \* 1-/2-/3-point calibration (best fit lines) Operating modes: - Calimatic automatic buffer recognition Input of individual buffer values Product calibration - Data entry of premeasured electrodes Drift check\*: fine / standard / coarse Calimatic buffer sets: \* Fixed buffer sets: 1 Mettler-Toledo 2.00 / 4.01 / 7.00 / 9.21 2 Merck/Riedel 2.00 / 4.00 / 7.00 / 9.00 / 12.00 3 DIN 19267 1.09 / 4.65 / 6.79 / 9.23 / 12.75 4 NIST standard 4.006 / 6.865 / 9.180 5 Techn. buffers to NIST 1.68 / 4.00 / 7.00 / 10.01 / 12.46 Manually enterable buffer set with max, three buffer tables (Additional function SW 700-002) Nom. zero \* pH 0 ... 14; calibration range  $\Delta$ pH =  $\pm$  1 Nom. slope (25 °C) \* 25 ... 61 mV/pH; calibration range 80 ... 103 % Viso \* -1000 to +1000 mV **Calibration record** Recording of: zero, slope, Viso, response time, calibration method with date and time **Statistics** Recording of: zero, slope, V<sub>iso</sub>, response time, glass and reference impedance with date and time of the last three calibrations and the First Calibration Sensocheck Glass electrode: Automatic monitoring of glass and reference electrode, message can be switched off ISFET electrode: Monitoring of ISFET parameters and reference electrode Sensoface Provides information on the sensor condition:

Zero/slope, response time, calibration interval,

Sensocheck, sensor wear (ISM only)

# **Specifications**

\*\*\*\*)

at 20 °C, doubles every 10 K

Sensor network diagram	Graphical representation of sensor parameters in a network diagram: slope, zero, reference impedance, glass impedance, response time, cal timer, sensor wear (ISM only)
Sensor monitor	Direct display of measured values from sensor for validation pH input / ORP input / glass el. impedance / ref. el. impedance / RTD / temperature
Wear monitor	Display of wear parameters Sensor load / sensor operating time / autoclaving cycles / CIP cycles / SIP cycles / maximum process temperature
ISM	Intelligent Sensor Management Plug & Measure Display of sensor data: manufacturer, production date, calibration date, wear data Enhanced diagnostic capabilities
KI recorder (Additional function SW 700-001)	Adaptive representation of a process sequence with monitoring and signaling of critical parameters
Adaptive calibration timer	*Automatic adjustment of calibration interval (Sensoface signal), depending on measured values
ServiceScope * (Additional function SW 700-004)	Monitoring of glass / reference electrode inputs for overdrive, graphical representation
Tolerance adjustment (Additional function SW 700-005)	Tolerant calibration/adjustment, tolerance limits adjustable graphical representation of zero and slope for the last 40 calibrations/adjustments
*) User-defined  **) To IEC 746 Part 1, at no  ***) ± 1 count, plus sensor 6	ominal operating conditions error

# **Specifications**

### **General data**

**Explosion protection** 

(Module pH 2700iX only)

Emitted interference Immunity to interference

**EMC** 

**Lightning protection** 

Nominal operating conditions

Transport/ Storage temperature

**Terminals** 

See rating plate: KEMA 04 ATEX 2056

ATEX: II 2 (1) GD EEx ib [ia] IIC T4 T 70 ° FM: IS, Class I, Div 1, Group A, B, C, D T4

NI, Class I, Div 2, Group A, B, C, D T4

NAMUR NE 21 and

EN 61326 VDE 0843 Part 20 /01.98

EN 61326/A1 VDE 0843 Part 20/A1 /05.99

Class B Industry

EN 61000-4-5, Installation Class 2

 $\begin{array}{lll} \mbox{Ambient temperature} & -20 \ ... \ +55 \ ^{\circ}\mbox{C (Ex: max. } +50 \ ^{\circ}\mbox{C)} \\ \mbox{Relative humidity} & 10 \ ... \ 95 \ \% \ not \ condensing \\ \end{array}$ 

-20 ... +70 °C

Single wires and flexible leads up to 2.5 mm² (AWG 14)

### **Annex:**

## Minimum measuring spans for current outputs

The pH 2700i(X) module is a measuring module. It does not provide current outputs. Current outputs are provided by the M 700 BASE (basic device) or by communication modules (e.g. Out, PID). The corresponding parameters must be set there.

The **minimum current span** shall prevent that the resolution limit of the measurement technology (± 1 count) is seen in the current.

### pH 2700i(X) module

рН	1.00
ORP	100.0
°C	10.0
mV	100.0
rH	1.00
°F	10.0

### **Calculation Block pH/pH**

Diff pH	1.00
Diff ORP	100.0
Diff °C	10.0

Mettler-Toledo

°C	рН				
0	2,03	4,01	7,12	9,52	
5	2,02	4,01	7,09	9,45	
10	2,01	4,00	7,06	9,38	
15	2,00	4,00	7,04	9,32	
20	2,00	4,00	7,02	9,26	
25	2,00	4,01	7,00	9,21	
30	1,99	4,01	6,99	9,16	
35	1,99	4,02	6,98	9,11	
40	1,98	4,03	6,97	9,06	
45	1,98	4,04	6,97	9,03	
50	1,98	4,06	6,97	8,99	
55	1,98	4,08	6,98	8,96	
60	1,98	4,10	6,98	8,93	
65	1,99	4,13	6,99	8,90	
70	1,99	4,16	7,00	8,88	
75	2,00	4,19	7,02	8,85	
80	2,00	4,22	7,04	8,83	
85	2,00	4,26	7,06	8,81	
90	2,00	4,30	7,09	8,79	
95	2,00	4,35	7,12	8,77	

Merck/Riedel

°C	рН				
0	2,01	4,05	7,13	9,24	12,58
5	2,01	4,04	7,07	9,16	12,41
10	2,01	4,02	7,05	9,11	12,26
15	2,00	4,01	7,02	9,05	12,10
20	2,00	4,00	7,00	9,00	12,00
25	2,00	4,01	6,98	8,95	11,88
30	2,00	4,01	6,98	8,91	11,72
35	2,00	4,01	6,96	8,88	11,67
40	2,00	4,01	6,95	8,85	11,54
45	2,00	4,01	6,95	8,82	11,44
50	2,00	4,00	6,95	8,79	11,33
55	2,00	4,00	6,95	8,76	11,19
60	2,00	4,00	6,96	8,73	11,04
65	2,00	4,00	6,96	8,72	10,97
70	2,01	4,00	6,96	8,70	10,90
75	2,01	4,00	6,96	8,68	10,80
80	2,01	4,00	6,97	8,66	10,70
85	2,01	4,00	6,98	8,65	10,59
90	2,01	4,00	7,00	8,64	10,48
95	2,01	4,00,	7,02	8,64	10,37

DIN 19267

$^{\circ}$ C	рН				
0	1,08	4,67	6,89	9,48	13,95*
5	1,08	4,67	6,87	9,43	13,63*
10	1,09	4,66	6,84	9,37	13,37
15	1,09	4,66	6,82	9,32	13,16
20	1,09	4,65	6,80	3,27	12,96
25	1,09	4,65	6,79	9,23	12,75
30	1,10	4,65	6,78	9,18	12,61
35	1,10	4,65	6,77	9,13	12,45
40	1,10	4,66	6,76	9,09	12,29
45	1,10	4,67	6,76	9,04	12,09
50	1,11	4,68	6,76	9,00	11,98
55	1,11	4,69	6,76	8,96	11,79
60	1,11	4,70	6,76	8,92	11,69
65	1,11	4,71	6,76	8,90	11,56
70	1,11	4,72	6,76	8,88	11,43
75	1,11	4,73	6,77	8,86	11,31
80	1,12	4,75	6,78	8,85	11,19
85	1,12	4,77	6,79	8,83	11,09
90	1,13	4,79	6,80	8,82	10,99
95	1,13*	4,82*	6,81*	8,81*	10,89*

<sup>\*</sup> extrapoliert / extrapolated / extrapolée

NIST Standard (DIN 19266: 2000-01)

°C	рН			
0				
5	1.668	4.004	6.950	9.392
10	1.670	4.001	6.922	9.331
15	1.672	4.001	6.900	9.277
20	1.676	4.003	6.880	9.228
25	1.680	4.008	6.865	9.184
30	1,685	4.015	6.853	9.144
37	1,694	4.028	6.841	9.095
40	1.697	4.036	6.837	9.076
45	1.704	4.049	6.834	9.046
50	1.712	4.064	6.833	9.018
55	1.715	4.075	6.834	9.985
60	1.723	4.091	6.836	8.962
70	1.743	4.126	6.845	8.921
80	1.766	4.164	6.859	8.885
90	1.792	4.205	6.877	8.850
95	1.806	4.227	6.886	8.833

#### Note:

The table above only serves for orientation purposes.

The actual pH values of the individual batches of the reference materials are documented in a certificate of an accredited laboratory. This certificate is supplied with the respective buffers.

Techn. Puffer nach NIST / According to NIST / Suivant NIST

°C	рН			
0	4.00	7.14	10.30	
5	4.00	7.10	10.23	
10	4.00	7.04	10.11	
15	4.00	7.04	10.11	
20	4.00	7.02	10.05	
25	4.01	7.00	10.00	
30	4.01	6.99	9.96	
35	4.02	6.98	9.92	
40	4.03	6.98	9.88	
45	4.05	6.98	9.85	
50	4.06	6.98	9.82	
55	4.07	6.98	9.79	
60	4.09	6.99	9.76	
65	4.09 *	6.99 *	9.76 *	
70	4.09 *	6.99 *	9.76 *	
75	4.09 *	6.99 *	9.76 *	
80	4.09 *	6.99 *	9.76 *	
85	4.09 *	6.99 *	9.76 *	
90	4.09 *	6.99 *	9.76 *	
95	4.09 *	6.99 *	9.76 *	

<sup>\*</sup> Values complemented


# **Buffer sets to be entered: SW 700-002**

Select menu: Parameter setting/System control/Buffer table Individual buffer set (with 3 buffer solutions) for pH measurement

#### **Buffer table**

You can enter an individual buffer set. To do so, you enter 3 complete buffer solutions in ascending order (e.g. pH 4, 7, 10) for the correct temperature (range 0 ... 95 °C, 5 °C steps).

<u>Distance between buffers in the whole temperature range</u>: min. 2 pH units. Then this buffer set is available as "Table" in addition to the permanently set standard buffer solutions.



The special buffer set is selected as follows:

Parameter setting/Module pH/Cal preset values/Calimatic buffer/Table.

# Parameter setting menu





### **Parameter setting**

Activated from measuring mode: Press **menu** key to select menu.

Select parameter setting using arrow keys, confirm with **enter**.

#### Administrator level

Access to all functions, also passcode setting. Releasing or blocking function for access from the Operator level.

#### Operator level

Access to all functions which have been released at the Administrator level. Blocked functions are displayed in gray and cannot be edited.

#### Viewing level

Only display, no editing possible!

System control	
Memory card (Option)  Register Logbook Register recorder Decimal separator Card full Formatting	Menu only appears with SmartMedia Card inserted.  Make sure that it is a <u>memory card</u> , not an <u>update</u> card.  Commercially available SmartMedia cards must be formatted before they can be used as memory card.
Copy configuration	The complete configuration of an analyzer can be written on a SmartMedia card. This allows transferring all device settings - except options and passcodes - to other devices with identical equipment.
Parameter sets	2 parameter sets (A,B) are available in the analyzer. The currently active parameter set is read on the display. Parameter sets contain all settings except: Sensor type, Options, System control settings Up to 5 parameter sets (1, 2, 3, 4, 5) are available when a SmartMedia card (Option) is used.
Function control matrix	Selecting the control element for the following functions: - Parameter set selection - KI recorder (Start/Stop) - Favorites menu (selected diagnostics functions) - EC 400 (fully automated probe controller)
Time/date	Selecting the display format, entry
Meas. point description	Can be called up in the diagnostics menu.
Release of options	A TAN is required to release an Option.
Software update	Software update from SmartMedia card (update card)
Logbook	Selecting events to be recorded
Buffer table	Entering own buffer set for automatic calibration
Factory setting	Resetting all parameters to factory setting
Passcode entry	Editing the passcodes

# Parameter setting menu



### **Display settings: FRONT module**

#### Languages

### Measurement display

- Main display
- Display format
- Viewing angle

Representation of measured values on the display:

- Selecting the number of primary values displayed (one or two)

Option, 2-channel, selection of process variable, start and end

- Decimal places

#### Measurement recorder

Time base

- Zoom function
- Min/Max display

Option. See more detailed "Options" manual

#### KI recorder

### Signal outputs and inputs, contacts: BASE module

#### Output current I1, I2 Process variable

- Characteristic
- Output (0/4 20 mA)
- Output filter
- Behavior during messages
  - Function check
    - --- Currently meas. value
    - --- Last meas, value
    - --- Fixed 22 mA
  - 22 mA message

2 current outputs, separately adjustable

#### Behavior during messages

Output current



#### Contact K4

- Contact type
- ON delay
- OFF delay

#### NAMUR Failure

#### Contacts K3, K2, K1

- Usage
  - Maintenance request
  - Function check
- Limit value (adjustable)

  - Parameter set B active

  - USP output
  - KI recorder active
- Contact type
- ON delay
- OFF delay

#### Factory setting:

K3: Maintenance request, K2: Function check, K1: Limit value

- Variable, limit value, hysteresis, effective direction, ...
- Rinse contact (adjustable) Rinsing interval, lead times, rinse duration, logbook entry, ...

#### Inputs OK1, OK2

- OK1 usage
  - Signal level

Optocoupler - signal inputs

Off, function check

active level switchable from 10 to 30 V or < 2 V. resp. For OK2 see System control/Function control matrix

# Parameter setting menu



### pH 2700i(X) module

#### Input filter

#### Sensor data

- Sensor type
- Temperature detection Selection (automatic for ISM) for meas / cal
- Sensoface
- Sensor monitoring

#### Details

- Slope
- Zero
- Sensocheck ref. el.
- Sensocheck glass el.
- Response time
- Sensor wear
- CIP counter
- SIP counter
- Autoclaving counter
- Sensor operating time

#### Cal preset values

- Calimatic buffer
  - Mettler-Toledo
  - Merck/Riedel
  - DIN 19267
  - NIST standard
  - NIST technical
  - Table
- Drift check
- Calibration timer
- Cal tolerance band
- ORP check

#### TC process medium

Selection: Off, linear, ultrapure water, table

Representation of measured values on the display:

- Selection (automatic for ISM)

#### ORP/rH value

- Reference electrode
- ORP conversion to SHE
- Calculate rH with factor

#### **Delta function**

#### Messages

- pH value
- ORP value
- rH value
- Temperature
- mV value

#### **Devaluate ISM sensor**

# Calibration menu



## pH 2700i(X) module

Calimatic Entry of buffer values Product calibration Data entry **ORP** calibration

# **Maintenance menu**



#### **BASE** module

Current source Output current definable 0 ... 22 mA

## pH 2700i(X) module

Sensor monitor pH / ORP input, RTD, Temp, Impedance glass + ref. el.

Temp probe adjustment Compesating for lead length

# **Diagnostics menu**



List of all warning and failure messages Message list

Meas, point description

Loabook

**Device description** Hardware version, Serial no., (Module) Firmware, ISM, Options

### FRONT module

Module diagnostics Display test Keypad test

#### **BASE** module

Module diagnostics Input/output status

### pH 2700i(X) module

Module diagnostics Internal function test

Servicescope pH input signal: Displays the noise levels over the time Sensor monitor Shows the values currently measured by the sensor

Cal record Data of last adjustment / calibration Cal record ORP Data of last ORP adjustment / calibration

**Sensor network diagram pH** Graphical representation of the sensor parameters Sensor wear monitor Current sensor wear, No. of CIP/SIP/autoclaving cycles Statistics

Displays first calibration and deviations of last 3 calibrations

pH 2700i(X)

#### A

Adaptive cal timer 67, 92 Adjustment 39 Administrator level 57 Audit Trail log 8 Autoclaving counter (ISM only) 22

#### В

Buffer sets to be entered 105 Buffer tables 99

#### C

Cal record 93

Cal tolerance band 67

Cal tolerance band, Program flow 65

Calculation Blocks 86

Calibration 38

Calibration by entering data from premeasured electrodes 50

Calibration methods 42

Calibration timer 67, 92

Calibration with manual entry of buffer values 46

Calimatic automatic buffer recognition 44

Calimatic buffer 67

Characteristics 76

CIP (Cleaning in Place) 26

Configuring the module 59

Contact type 83

Control signal 84

Current output: Settings 75

Current outputs 98

Current outputs: Characteristics 76

Current range is exceeded 79

Current span 98

### D

Data recording 14
Declaration of Conformity 3
Delta function 68, 71
Device description 10, 90
Device limits 72
Diagnostics 91-92
Diagnostics functions 89
Digital inputs 84
Display icons 115
Disposal 2

#### E

EC Declaration of Conformity 3 Electronic Signature 8 EMC 97 Enable / lock functions 58 Explosion protection 97

#### F

Factory settings 74
Failure 73, 80
Failure message 79
Favorites 24
FDA 21 CFR Part 11 8
First Calibration 40
First Calibration ISM 20
Function check 59, 80
Function control matrix 24
Functions 13

### Н

Hazardous-area application 9 Hysteresis 83

#### Ī

Icons 115
Input filter 62
Input/output status 90
Inserting the module 28
Intended use 8
ISFET sensor 30
ISFET zero adjustment 54
ISM - Intelligent Sensor Management 18
ISM diagnostics 23
ISM Plug and Measure 19
ISM sensor description 90
Isothermal potential 51

#### L

Lightning protection 97 Limit value 83 Locking a function 58 Logarithmic output curve 77 Logbook 74, 89

#### M

M 700 BASE 15
M 700 FRONT 12, 14
Maintenance 56, 73
Maintenance request 80
Maintenance request message 79
Max. device limits 72
Measured values 75
Measurement display settings 36
Menu groups 13
Menu items 13
Menu selection 34
Menu structure 34

Message icons 73
Message list 73, 89
Message when the current range is exceeded 79
Messages 72-73
Minimum measuring spans for current outputs 98
Modular concept 11
Module diagnostics 90-91
Module equipment 15
Monitoring functions for calibration 51

#### Ν

NAMUR signals 79-80

#### 0

OK inputs 84
OK1,OK2 inputs 84
One-point calibration 40
Operator level 57
ORP adjustment 52
ORP measurement 32
ORP related to the standard hydrogen electrode (SHE) 52
ORP/rH value 68, 71
Output current 75
Output filter 78
Overview of menu selection 116

#### P

Parameter sets 14, 85

Parameter sets: Signal via relay contact 85 Parameter sets: Switching via OK2 85 Parameter setting: Cal preset values 64

Parameter setting: Default settings and selection range 68

Parameter setting: ISM 21

Parameter setting: Limit value 83

Parameter setting: Locking a function 58

Parameter setting: Messages 72

Parameter setting: Operating levels 57 Parameter setting: ORP/rH value 71 Parameter setting: Relay contacts 82 Parameter setting: Sensor data 60

Parameter setting: TC process medium 69

Parameter tables (Excel) 17

Passcode entry 35

pH sensor monitoring adjustable 60

Predictive maintenance 22 Product calibration 48

#### R

Reference electrode types 52 Relay contacts 80 Relay contacts: Protective wiring 81 Release of options 66 Resolution limit 98 Return of products 2

### S

Safety information 9
Secondary displays 24, 36
Select favorites 25
Sensocheck - Sensor monitoring 61
Sensocheck, Sensoface 61
Sensoface 60
Sensoface criteria 61
Sensor connection 29
Sensor data 62
Sensor monitor 56, 91
Sensor monitoring details 21, 60
Sensor network diagram 93

Sensor replacement 40 Sensor wear monitor (ISM only) 23 ServiceScope 91 Setting diagnostics messages as favorite 24 Short description 12 SIP (Sterilize in Place) 26 SmartMedia card 14-15 Softkeys 24, 36 Software version 10 Specifications 94 Standard hydrogen electrode 53 Statistics 93 SW 700-105: Activation 66 Switching level 84 System control 74 T TC process medium 68-69 Temp probe adjustment 56 Temperature compensation during calibration 41 Temperature compensation of process medium 70 Temperature dependence of commonly used reference systems 53 Terminal plate 27 Test possibilities 90 Three-point calibration 40 Time constant 78

#### V

Viewing level 57

Typical wirings 29

Trademarks 2

Tolerance adjustment 64, 92

Two-point calibration 40

### W

Warranty 2 Wiring examples 29

## Z

Zero point 51

Icon	Explanation of icons important for this module
<b>♂ ism</b>	The analyzer is in measuring mode, an ISM sensor is connected.
	The analyzer is in calibration mode. Function check is active.
M ADLD	The analyzer is in maintenance mode. Function check is active.
■ ←	The analyzer is in parameter setting mode. Function check is active.
<b>⊘</b> <sub>dia</sub>	The analyzer is in diagnostics mode.
NAMUR signals	Function check. The NAMUR "function check" contact is active (factory setting: BASE module, contact K2, N/O contact). Current outputs as configured:  • Currently meas. value: The currently measured value appears at the current output  • Last measured value: The last measured value is held at the current output  • Fix 22 mA: The output current is at 22 mA  Failure: The NAMUR "failure" contact is active (factory setting: BASE module, contact K4, N/C contact). To view error message, call up: Diagnostics menu/Message list  Maintenance: The NAMUR "maintenance request" contact is active (factory setting: BASE module, contact K2, N/O contact). To view error message, call up: Diagnostics menu/Message list
<b>I</b> man	Temperature detection by manual input
*	Calibration is performed
¥	Calibration - Step 1 of product calibration has been executed. The analyzer is waiting for the sample value.
TC	Calibration: Temperature compensation for process medium is active (Linear/Ultrapure water/Chart)
Δ	Delta function is active (Output value = measured value – delta value)
۵	In the plaintext display in front of a menu line: Access to next menu level with <b>enter</b>
Ĥ	In the plaintext display in front of a menu line when it has been blocked by the Administrator against access from the Operator level.
	Designates the module slot (1, 2 or 3), allowing the clear assignment of measured-value/parameter displays in the case of identical module types.
<b>₽</b> B	Indicates the active parameter set (The analyzer provides two parameter sets A and B. Up to 5 sets can be added using additional functions and SmartMedia card.)

# **Menu selection**

	Calibration and adjustment	38
	Calimatic: automatic calibration	44
	Manual entry of buffer values	46
	Product calibration	48
	Data entry: premeasured electrodes	50
	ORP calibration	52
	ISFET zero adjustment	
llll	Maintenance	
maint	Autoclaving counter (ISM)	
	Parameter setting	
<u>om</u> par	Input filter	62
	Sensor data	62
	Cal preset values	64
	TC process medium	69
	ORP/rH value	71
	Delta function	71
	Messages	
	Current outputs, contacts, OK inputs (BASE)	75
(V)	Diagnostics	91
dlag	Module diagnostics	91
	ServiceScope	91
	Sensor monitor	91
	Adaptive calibration timer	
	Cal record	
	Sensor network diagram	
	Statistics	
	Tolerance adjustment	
	Set favorite	24

Order number: 52 121 276